

## LBB 3537/10

### Chairman Priority Control Panel

The chairman priority panel incorporates a priority button and an LED indicator. This unit is used in combination with the LBB 3537/00 Microphone with Control Panel to create a chairman position. When the priority button is pressed, all currently active delegate microphones are temporarily switched off, (dependent on CCU setting) thus giving the chairman priority microphone status over other delegates. The chairman priority panel can be connected to Multi-Purpose Connection Unit LBB 3540/15, or to one input of the Dual Audio Interface Unit LBB 3535/00.



#### Controls and indicators

- 'Microphone on' indicator (red LED)
- Priority key

#### Interconnection

- 2 m (78.74 in) cable terminated with 8-pole 262° DIN-type plug

#### Technical data

Mounting	click-to-fit in a 2 mm (0.08 in) thick metal panel (secured using 2 screws)
Dimensions (H x W)	front panel 40 x 120 mm (1.57 x 4.72 in) (built-in depth 30 mm (1.2 in))
Weight	approx. 125 g (0.28 lb)
Colour	charcoal (PH 10736)